

DIMEZE™

USB 2.1A POWER ADAPTOR MODULE INSTRUCTION MANUAL



SPECIFICATIONS


Model Number	DZ1G2.1USB
Supply Voltage Range	220 – 240Vac, 50Hz
Nominal Output Voltage	5.0Vdc ±5%
Nominal Output Current	2.1A @ 5.0Vdc
Standby Current	< 0.1mA
Wall Plate Compatibility	Fits all Clipsal Wall 30 Series aperture / Compatible wall plates
Usage	Charging Portable USB Power Devices Only; DO NOT use for Data Transmission
Suitable for Charging	Compatible with Apple® and Android™ devices, including Smartphones, Tablets, Music Players (MP3/MP4 Players), e-Readers
Operation Temperature	5 - 40°C
Humidity	Indoor Use Only, 15 – 85% Non-Condensing
Wire Size	1 x 2.5mm ² or 2 x 1.5mm ²
Complies With	IEC Application Pending (Product Certificate ready by July 10th)
Repair	This product does not contain user serviceable parts

Installation Instructions

The product must be used in conjunction with an accessible isolator or MCB. Ensure that the power has been turned off at the circuit breaker (MCB) before attempting installation or changing the USB module. Suitable for use as a charging device only – DO NOT use for Data Transmission. All wiring should be carried out by a licensed / registered electrician.

WIRING

DZ1G2.1USB fitted to an extraswitch socket



Note Illustration of USB power adaptor module is installed to a wall plate. Dimmer module and wall plate not included

Warning Notes

The DIMEZE™ USB power module is a solid state device, 240V will be present at the load even when the dimmer is switched off. The power must be switched off at the Circuit Breaker (MCB) to isolate the circuit before installation. The power module must be fitted to a Wall Plate and installed on a suitable enclosure (mounting block or flush box). The input terminals and wires should not be accessible when the product is being used.

Warranty Statement

The DIMEZE™ USB power module is guaranteed for a period of 1 year from the date of purchase against defects in workmanship and materials. Defects will be rectified by replacement of the product. This warranty becomes null and void if in our opinion the product has been misused, incorrectly installed, tampered with, or subject to power surges. The warranty does not include any labor or other associated expenses that may be involved in removal or installation of the production. To obtain a replacement under this guarantee, return the goods (prepaid) to the place of purchase (proof of purchase must be supplied).



Legend Tech International Holdings Limited

General Agency of **DIMEZE™**

www.legendtech.com.hk